

4" Square Plenum Boxes with Air-Tight Conduit K.O.S



Material: Galvanized Steel

Application: These 4" square boxes with conduit knockouts are installed in walls or ceilings for lighting fixtures, switches, receptables or other outlet devices. Square boxes are used to bring power to a number of electrical devices where multiple conductor runs are split in two or more directions.

Advantages: Can be surface or flush mounted when multidirectional conduit runs are necessary. Red painted boxes are also available to easily distinguish fire alarm circuits.

Field Names: 4S Box, 1900 box, 1900 electrical box, 1900 junction box, conduit box, J-box, concentric box, conduit junction box, outlet box, drywall mud box, 4" square box, 4" square junction box, 4" square outlet box, standard 1900 box, 1900 plenum box, standard 1900 plenum box, vapor tight box, fire alarm box.



ZQ52151-SVT



ZQ52151-3/4-VT



ZQ52171-SVT



ZQ52171-3/4-VT



ZQ52171-3/4-1VT



ZQ52171-1-VT



ZQ52181-SVT



ZQ53151-SVT



ZQ53171-SVT



ZQ53C1-VT



ZQ52C1-VT

Catalog Number	Description	Sides	Knockouts Bottom	Cubic Inches	Ship Case	Weight/ Case
BOXES						
ZQ52151-SVT	1-1/2" deep - Drawn	(8)-1/2" & (4)-3/4"	(3)-1/2" & (2)-3/4"	21.0	50	32.5
ZQ52151-3/4-VT	1-1/2" deep - Drawn	(8)-3/4"	(3)-1/2" & (2)-3/4"	21.0	50	9.5
ZQ52171-SVT	2-1/8" deep - Drawn	(8)-1/2" & (4)-3/4"	(3)-1/2" & (2)-3/4"	30.3	25	37.5
ZQ52171-3/4-VT	2-1/8" deep - Drawn	(8)-3/4"	(3)-1/2" & (2)-3/4"	30.3	25	19.5
ZQ52171-3/4-1VT	2-1/8" deep - Drawn	(4)-1" & (4)-3/4"	(2)-1/2" & (2)-3/4"	30.3	25	19.5
ZQ52171-1-VT	2-1/8" deep - Drawn	(8)-1"	(2)-1/2" & (2)-3/4"	30.3	25	18.75
ZQ52181-SVT	3-1/2" deep - Drawn	(8)-1/2" & (4)-3/4"	(3)-1/2" & (2)-3/4"	44.0	25	34.95
Extension						
ZQ53151-SVT	1-1/2" deep Extension Ring - Drawn	(8)-1/2" & (4)-3/4"	---	21.0	50	9
ZQ53171-SVT	2-1/8" deep Extension Ring - Drawn	(8)-1/2" & (4)-3/4"	---	30.3	25	19.5
ZQ53C1-VT	Flat open ring, double gasketed - Drawn	---	---	---	25	14
ZQ52C1-VT	4" Blank cover plenum flat	---	---	---	25	8