

Multi-Gang Device Rings - 1/2" & 3/4" Raised




Material: Galvanized Steel

Application: These gang box raised covers are used when multiple electrical or low voltage devices must be installed in finished wall applications. Gang boxes accept all manufacturers' wallplates. Each cover fits corresponding box size and one box size smaller.

Advantages: Gang box raised device covers allow the installer to mount multiple devices in one box location and attach finished wallplates flush with interior drywall plaster or tile surfaces.

Field Names: Multi gang plaster ring, mud ring, tile ring, drywall ring, device ring, device cover, plaster frame.


UL Number: E526989 (1/2" raised not UL Listed)




ZQGBDC-122
ZQGBDC-342(821)




ZQGBDC-123
ZQGBDC-343(822)




ZQGBDC-124
ZQGBDC-344(823)




ZQGBDC-125
ZQGBDC-345(824)



ZQGBDC-126
ZQGBDC-346(825)



ZQGBDC-127
ZQGBDC-347(826)



ZQGBDC-128
ZQGBDC-348(827)



ZQGBDC-129
ZQGBDC-349(828)

Catalog Number	Width	Description	Depth	Cubic Inches	Ship Case	Weight/ Case
ZQGBDC-122	7 -1/16"	2 gang	1/2"	8	20	10
ZQGBDC-123	8 -7/8"	3 gang	1/2"	17	20	11
ZQGBDC-124	10 -11/16"	4 gang	1/2"	21.5	20	12
ZQGBDC-125	12 -1/ 2"	5 gang	1/2"	26	10	7
ZQGBDC-126	14 -5/16"	6 gang	1/2"	30.5	10	8
ZQGBDC-127	16 -1/ 8"	7 gang	1/2"	35.5	5	6
ZQGBDC-128	17 -15/ 16"	8 gang	1/2"	40.8	5	8
ZQGBDC-129	19 -3/4"	9 gang	1/2"	45.8	5	9
ZQGBDC-342(821)	7 -1/16"	2 gang	3/4"	11	20	11
ZQGBDC-343(822)	8 -7/8"	3 gang	3/4"	17	20	12
ZQGBDC-344(823)	10 -11/16"	4 gang	3/4"	21.5	20	14
ZQGBDC-345(824)	12 -1/ 2"	5 gang	3/4"	26	10	8
ZQGBDC-346(825)	14 -5/16"	6 gang	3/4"	30.5	10	9
ZQGBDC-347(826)	16 -1/ 8"	7 gang	3/4"	35.5	5	7
ZQGBDC-348(827)	17 -15/ 16"	8 gang	3/4"	40.8	5	9
ZQGBDC-349(828)	19 -3/4"	9 gang	3/4"	45.8	5	10