

## 4" x 2" Handy Boxes and Extension




**Material:** Galvanized Steel

**Application:** These handy utility boxes are used for convenience outlets, switches and small junction boxes in exposed work applications. They are great for appliances and machinery. Extension rings are available to provide a means of adding additional wire capacity or to serve as outlet boxes for surface conduits.


**Advantages:** Handy utility boxes have a small, rectangular design that allow for power outlets and switches to be installed in small places. They can easily be customized with special holes or knockouts for OEM applications. Handy utility boxes with brackets are available when boxes must be mounted directly to wood or metal studs.

**Field Names:** Handy box, utility box, 2x4 box, switch box, device box, handy box extension ring, utility box extension ring.


**UL File No:** E526989(ZQG19280, ZQG19282 not UL listed)




ZQG19280(650)




ZQG19281(660)




ZQG19281-3/4(663)



ZQG19282



ZQG19281-TS(662)



ZQHSB-1-50



ZQG19281-E(665)

Catalog Number	Description	Knockouts		Cubic Inches	Ship Case	Weight/ Case
		Sides	Bottom			
BOXES						
ZQG19280(650)	1-1/2" deep 1/2" KO with raised ground emboss - Drawn	(8) - 1/2"	(2) - 1/2"	11.5	50	18.5
ZQG19281(660)	1-7/8" deep 1/2" KO with raised ground emboss - Drawn	(8) - 1/2"	(2) - 1/2"	13.0	50	24
ZQG19281-3/4(663)	1-7/8" deep 3/4" KO with raised ground emboss - Drawn	(6) - 3/4"	(1) - 3/4"	13.0	50	24
ZQG19281-TS(662)	1-7/8" deep 1/2" KO with raised ground emboss and TS bracket - Drawn	(5) - 1/2"	(2) - 1/2"	13.0	50	24
ZQHSB-1-50	1-1/2" deep 1/2" KO - Welded	(8) - 1/2"	(3) - 1/2"	11.5	50	23
ZQG19282	2-1/8" deep 1/2" KO with raised ground emboss - Drawn	(8) - 1/2"	(2) - 1/2"	16.5	50	24
EXTENSION						
ZQG19281-E(665)	1-7/8" deep extension - Drawn	(8) - 1/2	---	13.0	50	30