

4-11/16" Industrial Covers



Material: Galvanized Steel

Application: These 1/2" raised surface covers with included screws and nuts are used to mount electrical devices on 4-11/16" square boxes in industrial settings. They are also used when boxes are surface mounted or positioned in exposed work applications.

Advantages: Allow for a quick installation of devices and switches on steel covers before they are mounted onto a box.

Field Names: Raised surface cover, exposed work cover, crushed-corner cover, surface cover, device cover, switch cover, raised switch cover, 5S device cover, 11B industrial cover, 11B raised surface cover, 11B cover, 4-11/16 cover.



Catalog Number	Description	Depth	Cubic Inches	Ship Case	Weight/Case
ZQ72C29	Blank Cover, 1/2" raised	1/2"	10.3	50	27.5
ZQ72C32	(1) Single Receptacle, 1.406" diameter	1/2"	10.3	50	15.5
ZQ72C35	(1) Toggle switch	1/2"	10.3	50	22
ZQ72C36	(2) Toggle Switches	1/2"	10.3	50	9.5
ZQ72C37	(2) Single Receptacle, 1.406" diameter	1/2"	10.3	50	23
ZQ72C38	(1) Duplex receptacle	1/2"	10.3	50	9.5
ZQ72C39	(2) Duplex receptacles	1/2"	10.3	50	23
ZQ72C40	(2) Single Receptacle, 1.62" diameter	1/2"	10.3	50	22
ZQ72C41	(1) Duplex & (1) Toggle Switch	1/2"	10.3	50	25
ZQ72C42	(1) 20 Amp Receptacle, 1.594" diameter	1/2"	10.3	50	25
ZQ72C44	(1) 30-50 Amp Receptacle, 2.141" diameter	1/2"	10.3	50	25
ZQ72C45	(1) 50 Amp Twist-lock Receptacle	1/2"	10.3	50	22.5
ZQ72C47	(1) Decorative or GFCI Receptacle	1/2"	10.3	50	12.5
ZQ72C48	(1) Decorative/GFCI & (1) Toggle Switch	1/2"	10.3	50	20
ZQ72C49	(2) Decorative/GFCI Receptacles	1/2"	10.3	50	22.5
ZQ72C50	(1) 30-60 Amp Receptacle, 2.441" diameter	1/2"	10.3	50	27
ZQ72C51	(1) Duplex & (1) Decorative/GFCI Receptacle	1/2"	10.3	50	20